

The Contrario Range

Xpresso

Example of 1 Contrario Xpresso equipped with CD/USB player and wireless receiver



Basic Equipment

RMS Power	70 Watts / 4 ohms - 100 Watts / 2 Ω	Bands EQ	Bass, Mid, Treble
Power Requirements	Operates on AC 220v	Outputs	Master volume control allows Xpresso to work like a mixer RCA Line Output (post fader) Output Speaker on Jack 6.35
Lead Battery	Built-in battery 9 Ah - 12 V Fast automatic battery charger integrated	More Information	Strap handle Dimensions: H53,5 x W27,5 x D28 cm / H21.1 x W10.8 x D11" Weight: 13 kg / 28.66 lbs Flight case in colour black
Working Time	3 -6 hours on built in battery / unlimited on AC main		
Inputs	Mixable inputs: 2 RCA Line control inputs 1 balanced MIC control input on Jack 6,35 1 balanced MIC control input + phantom power on XLR 12 volt input		

Options

Wireless System	2 UHF 16 frequency receivers possible: SDR-6216M
Player	2 players possible, choose between: CD/USB player: CD-456 Digital player: EM010PR Digital recorder: EM020R Record/Tape player: K7-EX-ED950
Talk over	Voice priority for wireless MIC